

Product Name: ZX153-026-PC4-QMS Samtec Breakout Adapter

Product Description: 26pins x 2 rows, 52 pin Samtec breakout adapter – Single Ended. Offering QMS-PC4 connectors on a single breakout adapter. Designed in 4 layer PCBoard with full access to all 52+8 PC4 power signals.

The Samtec GND pins are connected to the modules top/bottom fill & 2 inner GND planes for reduced crosstalk, xtalk, and improved signal integrity.

GND test point for direct connection.

Application: Bringup, testing, emulation, development, modular design evaluations

Mates with : Samtec QFS-026-PC4 -PC4 option

Pitch: 0.635mm (0.025") High Speed connector

Headers: 0.1" (2.54mm) center, 0.025" SQ with 0.22" (5.58mm) post height



1.4" (36mm)
1.88" (47.8mm)
1.8" (45mm)



2.0" (50mm)

QMS/QFS PC4 terminal (PC1 .. PC8) assignments – front view - 2 bank connector is shown



ZX153-026-PC4-QMS pin configuration

Top	Headers	J3	PC7	51	47	43	39	35	31	27	23	19	15	11	7	3	PC3
			PC5	49	45	41	37	33	29	25	21	17	13	9	5	1	PC1

Bottom	Headers	J4	PC8	52	48	44	40	36	32	28	24	20	16	12	8	4	PC4
			PC6	50	46	42	38	34	30	26	22	18	14	10	6	2	PC2

Header pin numbers refer to the SAMTEC connector pin number



Note
ALL ZEBAX products are RoHS compliant and Lead Free unless otherwise indicated.

ZEBAX TECHNOLOGIES
SANTA CRUZ, CA U.S.A (831) 222-0717
WWW.ZEBAX.COM

SPECIFIED DIMENSIONS ARE INCHES (MMD). ROHS COMPLIANT	ASSEMBLY DRAWING	
	ITEM: ZX153-026-PC4-QMS	
DESCRIPTION: Samtec breakout adapter 026 PC4 QMS		
CHECKED: M. MARINA	DRAWN: SLAVIK	REVISION: 1.0 SHEET: 1 OF 1

Notice
ALL ZEBAX TECHNOLOGIES DESIGN SPECIFICATIONS, DRAWINGS, PUBLICATIONS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." ZEBAX MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NO INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE.
Information furnished is believed to be accurate and reliable. However, Zebax Technologies assumes no responsibility for the consequences of use of such information or for any infringement of patents or other rights of third parties that may result from its use. Specifications mentioned in this publication are subject to change without notice. This publication replaces all other information previously supplied. Zebax Technologies products are not authorized as in life support devices or systems.